

## Manual Call Point FD3050



The Manual Call Point FD3050 is designed to release a signal for a fire condition to the Fire Control Panel upon manual activation by pressing on the specific place signed with arrows.

The unit is compatible with the requirements of the European Standard EN54-11; A1:2005.

### Technical data

**Electrical installation:**

- Through terminal for connecting wires with cross-section (0,5 - 1,5) mm<sup>2</sup>
- Built-in dry contact

**Supply voltage:**

- (10-30) VDC

**Degree of protection:**

- IP 40

Operational temperature range: -10 °C to +55 °C

Relative Humidity: (93±3)% at 40 °C

Dimensions: 98x96x51 mm

Weight of the manual call point: 0,150 kg

Material: ABS, red



Office building UniPOS,  
1 Efr. Nikola Paskalev Str., Mladost 1, Sofia 1748, Bulgaria  
Phone: +359 2 97 439 25, +359 2 97 444 69

47 San Stefano Str., Pleven 5800, Bulgaria  
Phone: +359 64 891 100

<http://unipos-bg.com/>